7000 series
master clock & bell signal

Pyramid Technologies

Master clock & bell signal

This system synchronizes 50 clocks and up to 15 bells off a single zone and is expandable to 4 bell zones. The master clock can handle a total of 300 events. An easy to use, ***plug and play*** system requires minimal set up time. The bell ringer is available in both 24 VDC and 0-220 VAC format. A one year manufacturer's warranty is included.

Features

- Automatic time correction within 2 minutes if power was to fail
- Automatic Daylight Savings Time adjustment
- 12 hour or 24 hour display for digital clocks
- Battery back-up
- Easy installation
- Low voltage 24 VDC bell system
- Schedules up to 300 events per week
- Software included for PC screen set-up
- Powers up to 15 bells/horns
- Expandable to multi-circuit bell system
- Expandable to run unlimted number of clocks
- Size: 6"h x 5"w x 1.75"d

Major Accessories

Software

Horns

Bell ringer

Clocks

Bells

Pyramid Technologies, 48 Elm St., Meriden, CT. 06450 USA Tel: **203.238.0550** fax: **203.634.1696**
Toll Free: **1.888.479.7264** **www.pyramidtechnologies.com** **MADE in the USA**

System Options

Pyramid Technologies

Single zone system



Multi-zone system

Options
7024
7110



Accessory Chart

Model 7000 clock-single zone bell ringer	7000	Single 24 VDC circuit directly powers up to 15 bells, BCD signal for 50 system clocks (200+ w/booster), RJ-45 connection, 3 button set-up
Model 7024 DC clock-multi zone bell ringer	7024	(4) 24 VDC (supplied) bell circuits-powers up to 15 bells total; serial computer connector, "Y" connector, 50' cable, software and 7000 master clock
Model 7110 AC clock-multi zone bell ringer	7110	(4) 0-220 VAC relays, 10 amps per circuit, up to 50 bells per zone, serial computer connector, "Y" connector, 50' cable, software and 7000 master clock
Clock booster	7050	Boost signal for 200 system clocks, daisy chain boosters for unlimited clocks
Y Connector	41270	"Y" connector
Coupler	41313	Coupler
50' Cable	41269	50' cable
100' Cable	41314	100' cable
2.5" Digital system clock white/black	41354/41355	110 VAC line card & prewired RJ-45 connector for above systems
4" Digital system clock white/black	41356/41357	110 VAC line card & prewired RJ-45 connector for above systems
12" Analog system clock	5200	110 VAC or 24 VDC, prewired RJ-45 connector for above systems
6" / 8" Bell	41361/41392	24 VDC
6" / 8" Bell	41397/41398	110 VAC
Horn	41362/41363	24 VDC/110 VAC

Tel: **203.238.0550** fax: **203.634.1696** Toll Free: **1.888.479.7264** **www.pyramidtechnologies.com**